

LoRa Alarm Unit - Battery Powered

OVERVIEW

The purpose of installing a LoRa based Alarm Unit on the premise is to:

- Show Emergency Alarm
- Show Alerts triggered from any backend application
- Alerts received as downlink messages over LoRa
- Multiple Alarm & LED Patterns can be configured

KEY FEATURES

- Configurable via OTA over LoRa
- 75 dB Buzzer Siren on Alerts received
- Multi-color LED Alerts
- LED-Button to manually stop the Alarm
- **Class A Device** with Secure Data Transmission
- **Battery Powered**
- Available with
 - Red Lens MTC-AU02 (**Red / Yellow LED**)
 - White Lens MTC-AU04 (**Multicolor LED**)

SPECIFICATIONS

Model No.	MTC-AU02, 04
Enclosure Size	95 x 95 x 40 mm
Net Weight	150 g
Ingress Protection	IP67
OTAA and ADR	Compliant
RF Output	14 dBm
Operating Temperature	-18°C to +55°C

MUTELCOR 



APPLICATIONS

- Control Rooms
- Manufacturing Units
- Villas & Apartments
- Commercial Complexes
- Senior Residences
- Offices
- Hospitals
- Shopping Malls
- Museums

LoRa Frequency	EU863-870 (CE-Certified) IN865-867 (ETA-Certified) US902-928 AU915-928 AS923 -1, -2, -3, -4 KR920-923
SF Supported	7 - 12
Voltage	3V (2 x AA-Lithium Battery)



LoRa Alarm Unit - Battery Powered

ALARM UNIT FUNCTIONALITY

- **Class A Device** with regular heartbeats
- Alarms are triggered by LoRa downlink messages
- LED Button-press stops Alarm locally and sends uplink confirmation via LoRa

MUTELCOR 

ALARM UNIT BEHAVIOR



- **Up to 4 Alarm-Types can be configured on the Device, based on the following parameters:**
 - LED Color (**GREEN ***, **YELLOW**, **RED**)
 - Customizable **multicolor** option
 - LED Behavior (OFF, ON, Flashing)
 - Buzzer Sound (OFF, ON, Beep)
 - Alarm Time Duration
- Each configured Alarm-Type is triggered by a specific LoRa downlink message
- Each Alarm-Type can be used to indicate different scenarios e.g. Alarm raised due to Panic Button Press, Temperature/ Humidity/CO₂ Threshold exceeded, etc.



* Only with MTC-AU04

