## LoRa Panic Button with Confirmation

#### **OVERVIEW**

# The purpose of installing a LoRa based Panic Button Security Solution on the premise is to:

- Raise Alarm in real time
- Emergency Alarm with Acknowledgement
- Notify Responders
- Seek instant Assistance

#### **KEY FEATURES**

- 5 Years Battery Life
- Dust- and Waterproof
- Accidental Push Protection
- Built-In Confirmation Alarm
- Alarm message on Button Press
- Regular Heartbeat with Battery Status
- Secure Data Transmission
- Configurable in real-time with OTA Commands

### **SPECIFICATIONS**

Model No.	MTC-PB01, 02
Enclosure Size	95 x 95 x 40 mm
Net Weight	184 g
Ingress Protection	IP67
Operating Temperature	-18°C to +55°C
RF Output	14 dBm
Battery Life	5 Years

### **MUTELCOR**



### **APPLICATION**

- Educational Institutions
- Villas/Apartments
- Manufacturing Units
- Shopping Malls
- Motels
- Mospitals
- Airports
- Banks
- Museums

LoRa Frequency	EU863-870 (CE-Certified) IN865-867 (ETA-Certified) US902-928 AU915-928 AS923 -1, -2, -3, -4 KR920-923
SF Supported	7 – 12
OTAA and ADR	Compliant
Voltage	3V (2 x AA-Alkaline Battery)

# LoRa Panic Button with Confirmation

#### **FUNCTIONALITY**



#### In case of an emergency, press the Button

- Device sends a wireless Alarm message over LoRa
- LED starts flashing RED and/or Buzzer starts beeping
- Device sends multiple Alarm messages for enhanced robustness
- Device awaits for an Alarm response from Backend Application

#### **CONFIRMATION-FUNCTIONALITY**



#### If Alarm response is received

- LED glows YELLOW (MTC-PB01)
- **●** LED glows **GREEN** (MTC-PB02)
- Buzzer stops beeping

#### If Alarm response is not received

- LED starts flickering in RED
- Buzzer starts alarming rapidly

# Configurable Parameters in case of received or missed Alarm response



- LED Color (None, **RED**,

  YELLOW, GREEN\*)
- LED Behavior (Constant, Flashing, Flickering, OFF)
- LED Active Time

- Buzzer(Constant, Toggling, OFF)
- Buzzer Active Time
- Response Waiting Time

#### **VARIANT PANIC BUTTON-OPTIONS**

- Standard Model (MTC-PB01) comes with Red Lens and LED color to glow YELLOW / RED
- 3-Color Model (MTC-PB02) comes with White Lens and LED color to glow GREEN / YELLOW / RED







\*Only with MTC-PB02

